




CE4P Series Photocell Dusk to Dawn Instructions



**Caution, risk of
electric shock.**

IMPORTANT INSTALLATION INFORMATION This product must be installed in accordance with the latest edition of Building Regulations and carried out by a qualified electrician in accordance with the latest IEE Wiring Regulations. Before commencing any installation or maintenance work, ensure that the mains supply is switched off and the appropriate MCB or fuse is isolated.

MAINS WIRING Cable colours are shown opposite.



The Photocell fitted to your Diamond LED floodlight provides an automatic turn on and off at dusk and dawn. You may also wish to incorporate a time clock into the supply cable feed if for instance it's used within a commercial premises only operating five days per week. Typical lux levels for turning on your floodlight are <20 Lux, off >80 Lux. Available in 30, 50, 80, 100 & 150 watt versions. Colour temperature 6000K, IP65, 100-240VAC, 50Hz, 1M cable.

Sanan LED/COB Chip.

Installation:

Due to physical constraints, it has been necessary to locate the Photocell near to the cable entry on some models. Although the cable entry would normally be located at the bottom of the fitting you must ensure that the photocell is pointing skywards. Only by having the Photocell visible to the sky can the correct dusk and dawn operation be guaranteed.